

▶▶ D2031系列直流滤波器



特征

- ◆ 双极共模滤波
- ◆ 增强差模抑制功能
- ◆ 非常高的共模和差模抑制比
- ◆ 适用于共模干扰非常强烈的现场

典型应用

- ◆ 消防报警设备
- ◆ 光伏产品
- ◆ 铁路自动化控制器
- ◆ 智能电力仪表

技术参数

额定电压	100VDC
工作频率	—
线-线耐压	200VDC
线-地耐压	500VDC
绝缘电阻	>100MΩ @100VDC
工作温升	<30℃@40℃
气候类别 (IEC 60068-1)	25/085/21


选型列表

产品型号	额定电流 (A)	外壳	连接端子		电路原理图
			通用	可选	
DTD2031-1-W20-B15	1	B15		—	
DTD2031-3-W20-B15	3	B15		—	
DTD2031-6-F8-D15	6	D15		—	
DTD2031-10-M6-D35	10	D35			
DTD2031-20-M6-D45	20	D45			
DTD2031-30-M6-D45	30	D45		—	
DTD2031-50-M6-D55	50	D55		—	


D2031系列直流滤波器

插入损耗


—— 共模 - - - - - 差模 (50 Ω / 50 Ω 测量系统 符合IEC/CISPR NO. 17)




DTD2031-1-W20-B15




DTD2031-3-W20-B15




DTD2031-6-F8-D15




DTD2031-10-M6-D35



DTD2031-20-M6-D45




DTD2031-30-M6-D45




DTD2031-50-M6-D55


外形尺寸(mm)




B15 (W20)




D15 (F8)




D35 (M6)



D45 (F8)



D45 (M6)



D55 (M6)

10